Explosion protection

Ex protection marking	ATEX: Ex db IIB+H2 T6 Gb
	IECEx: Ex db IIB+H2 T6 Gb
	CSA/CUS Class I Div 1 Group B, C + D
	CE ⁰⁵¹⁸

Technical data

Technology	measurement/small stainless steel flash chamber, spark ignition
Method	complies with: ASTM D56, ASTM D93
Measuring range	25 to 125 °C (77 to 257 °F)
Repeatability	± 1 °C or better
Reproducibility	≤ ASTM
Measuring cycle	measuring cycle typical 5 min or better
- Electrical data	
Nominal voltage	100 to 120 V AC 1 phase; 50/60 Hz 200 to 240 V AC 1 phase; 50/60 Hz
Maximum power consumption	less than 500 W
- Protection class	IP 65
- Ambient conditions	
Ambient temperature	operation -18 up to 40 °C (0 to 104 °F)
Ambient humidity	less than 90 %
Sample	
Quality	filtered 10 µm, without water or moisture
Consumption	0.9 to 6 l/h
Pressure at inlet	1.4 to 10 bar (20 to 150 psi)
Temperature at inlet	min. 10 °C below expected FP temperature ≤ 85 °C
Utilities	
 Instrument air Consumption 	
Purge	60 l/h at 10 seconds per cycle
Operation	24 to 30 l/h continuous
Pressure at inlet	24 to 30 l/h continuous 2.7 to 17.2 bar (40 to 250 psi)
·	

Analog outputs	Flash Point, sample temperature	
Digital outputs	sample FP alarm, analyzer maintenance warning, analyzer fault alarm	
Digital inputs	customer alarm, remote standby, stream switch, validation request	
Electrical data of signal outputs and inputs		
Analog outputs	up to 3 to 4-20 mA self powered and isolated, 1 is standard	
Analog inputs	optional	
Digital outputs	up to 3 dry contacts programmable, alarm critical, come read, alarm warning	
Digital inputs	up to 4 dry contact inputs	
User interfaces		
Display	7" color graphics	
Keyboard	5 button magnetic, no hot work permit required	
Connections		
Sample inlet	1/4" FNPT	
Sample outlet	1/4" FNPT	
Vent/Drain	1/4" FNPT	
Weight and dimensions		
Weight	approx. 228 kg (500 lbs)	
Dimensions (W x H x D)	approx. 940 x 1803 x 762 mm (37" x 71" x 30" in)	
Optional interfaces		
Analog outputs	optional, cell temperature	
MODBUS interface	TCP/IP or Serial/RTU MODBUS output available	

Signal outputs and inputs