

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

SmartOnline SUTX Series 3-Phase 220/380V, 230/400V, 240/415V 20kVA 20kW On-Line Double-Conversion UPS, Tower, Extended Run, SNMP Option

MODEL NUMBER: SUTX20K











3-phase UPS system protects connected mission-critical equipment against damage, downtime and data loss due to blackouts, brownouts, power surges and line noise.

Description

The SUTX20K SmartOnline® SUTX Series 3-Phase 220/380V, 230/400V or 240/415V 20kVA 20kW On-Line Double-Conversion UPS provides battery backup and AC power protection against power disturbances that can damage electronics or destroy data. It's recommended for critical data center, LAN/WAN and distributed server room applications.

The SUTX20K's Voltage and Frequency Independent (VFI) design allows continuous operation at any supported voltage at either 50 or 60 Hz. Zero transfer time to battery mode ensures no disruption to the attached loads. Automatic and Manual Bypass keeps connected equipment powered, even during overloads and UPS maintenance.

IGBT inverter technology produces output power with 1% total harmonic distortion (THD) to keep connected equipment functioning at its peak. A 3:1 crest factor safely supports a variety of loads, even those with wildly fluctuating power demands.

Managing the SUTX20K is simplified through the multi-language LCD interface, which displays critical operating conditions and diagnostic data, such as battery and load status. Four LEDs indicate bypass, line, battery and fault modes. A serial port allows connection to Tripp Lite's free local shutdown agent. A built-in card slot supports the optional WEBCARDLX network management card for network interface and remote monitoring and control.

Features

VFI True On-Line Double-Conversion 3-Phase UPS System

- Provides fully regulated sine wave AC output for critical data center, LAN/WAN and distributed server room applications
- +/-1% output voltage regulation in online and battery modes
- 1.0 unit power factor offers 20kVA/20kW output capacity, allowing for more connected devices
- Supports 380/220V, 400/230V or 415/240V at 50/60 Hz in continued operation
- Wide input voltage window (228-477V) minimizes battery use and prolongs battery life

Reliable Battery Backup with Expandable Runtime

• Supports half load for 33.4 min. and full load for 14.3 min. with standard internal battery

Highlights

- On-line double-conversion topology, VFI operation
- Automatic and Manual Bypass for enhanced reliability
- Add optional WEBCARDLX with latest version of PADM20 for enhanced remote management
- Internal batteries and expandable runtime options
- Paralleling capability of up to 4 units

Package Includes

- SUTX20K SmartOnline SUTX Series 3-Phase 220/380V, 230/400V, 240/415V 20kVA 20kW On-Line Double-Conversion UPS
- RS-232 (DB9) cable
- · Owner's manual



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

- Zero transfer time suitable for advanced network applications
- Expandable runtime with optional external battery packs, such as Tripp Lite's BP480V09
- Restarts automatically after lengthy power outages

IGBT Inverter Technology

- Produces output power with 1% THD to keep connected equipment functioning at its peak
- Low <5% THDi input rating and advanced IGBT rectifier enables 1:1 generator sizing, eliminating costly
 oversizing requirements for generators, breakers and cables

Paralleling Capability

• Connect up to 4 units in parallel configuration for fault tolerance or increased capacity up to 80kVA

Automatic and Manual Bypass

- Allows maintenance without removing power from attached loads
- · Increases system reliability

ECO Mode

• Operates at efficiency levels as high as 98% when input line conditions are favorable

Optional Network Management Card

- Optional WEBCARDLX (sold separately) with the latest version of PowerAlert Device Manager firmware (PADM20) provides enhanced remote management capabilities
- PADM20 and PowerAlert Element Manager (PAEM) form a powerful tool for expanding maintenance functions in large installations, including firmware update checks and backup and restoration of device configurations

Communications Ports

- DB9 port enables data-saving unattended shutdown when used with Tripp Lite's Power Alert software (available via free download at www.tripplite.com/poweralert)
- EPO port supports emergency shutdown in large facilities

Single, Compact Cabinet

May be installed with either single or dual AC sources for increased availability

Specifications

OVERVIEW		
-		
UPC Code	037332186737	
UPS Type	On-Line	
INPUT		
Rated input current (Maximum Load)	36.8A (220/380V) / 35.2A (230/400V) / 33.8A (240/415V)	
Nominal Input Voltage(s) Supported	220/380V 3-PH Wye; 230/400V 3-PH Wye; 240/415V 3-PH Wye	
Nominal Input Voltage Description	3-Phase Wye, 4 wire (L1, L2, L3, N, G)	
UPS Input Connection Type	Hardwire	
Input Circuit Breakers	40A 4 pole breaker (415V)	
Input Phase	3-Phase	



оитрит		
Output Volt Amp Capacity (VA)	20000	
Output Capacity (kVA)	20	
Output Watt Capacity (Watts)	20000	
Output kW Capacity (kW)	20	
Power Factor	1	
Crest Factor	3:1	
Nominal Voltage Details	Factory default output voltage is 230/400V	
Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	Automatic frequency selection	
Output Voltage Regulation (Line Mode)	+/-1%	
Output Voltage Regulation (Economy Line Mode)	+/- 10% of nominal voltage	
Output Voltage Regulation (Battery Mode)	+/-1%	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	Pure Sine wave	
Nominal Output Voltage(s) Supported	220/380V 3-PH Wye; 230/400V 3-PH Wye; 240/415V 3-PH Wye	
Output Receptacles	Hardwire	
Individually Controllable Load Banks	No	
BATTERY		
Full Load Runtime (min.)	14.3 min. (20kW)	
Half Load Runtime (min.)	33.4 min. (10kW)	
Expandable Battery Runtime	Supports extended runtime with optional external battery packs	
Expandable Runtime	Yes	
Expandable Runtime Description	External battery pack wiring is contractor supplied	
External Battery Pack Compatibility	BP480V09	
DC System Voltage (VDC)	+/- 240VDC	
Battery Recharge Rate (Included Batteries)	10 hours from 10 to 90%	
Battery Replacement Description	Hot-swappable, replaceable batteries	
VOLTAGE REGULATION		
Voltage Regulation Description	Online, double-conversion power conditioning	



ins continuous operation without using battery power during overvoltages to 477V (3-phase, 4-wire, wye), no output within 1% of nominal ins continuous operation without using battery power during brownout/undervoltage conditions to 228V (70% 300V (100% load) panel LCD with scroll and enter buttons offers display of UPS operating mode, plus voltage and frequency ation; LCD also reports a variety of alarm conditions such as Short circuit, Inverter fail and Over temperature; rts English, French, German, Russian, Portuguese, Spanish and Turkish language options tton turns UPS inverter on. OFF button turns UPS inverter off. LCD Display Control Buttons browse through lect items displayed on LCD screen. EPO (Emergency Power Off) button turns UPS output off and disables soutput -fail alarm can be silenced using alarm-cancel switch s signal a variety of operational conditions: low-battery, overload, shutdown, bypass and more Display: Displays normal AC input, on battery power and fault conditions
panel LCD with scroll and enter buttons offers display of UPS operating mode, plus voltage and frequency ation; LCD also reports a variety of alarm conditions such as Short circuit, Inverter fail and Over temperature; rts English, French, German, Russian, Portuguese, Spanish and Turkish language options tron turns UPS inverter on. OFF button turns UPS inverter off. LCD Display Control Buttons browse through elect items displayed on LCD screen. EPO (Emergency Power Off) button turns UPS output off and disables output. In alarm can be silenced using alarm-cancel switch as signal a variety of operational conditions: low-battery, overload, shutdown, bypass and more. Display: Displays normal AC input, on battery power and fault conditions.
ation; LCD also reports a variety of alarm conditions such as Short circuit, Inverter fail and Over temperature; rts English, French, German, Russian, Portuguese, Spanish and Turkish language options tton turns UPS inverter on. OFF button turns UPS inverter off. LCD Display Control Buttons browse through elect items displayed on LCD screen. EPO (Emergency Power Off) button turns UPS output off and disables output -fail alarm can be silenced using alarm-cancel switch s signal a variety of operational conditions: low-battery, overload, shutdown, bypass and more Display: Displays normal AC input, on battery power and fault conditions
ation; LCD also reports a variety of alarm conditions such as Short circuit, Inverter fail and Over temperature; rts English, French, German, Russian, Portuguese, Spanish and Turkish language options tton turns UPS inverter on. OFF button turns UPS inverter off. LCD Display Control Buttons browse through elect items displayed on LCD screen. EPO (Emergency Power Off) button turns UPS output off and disables output -fail alarm can be silenced using alarm-cancel switch s signal a variety of operational conditions: low-battery, overload, shutdown, bypass and more Display: Displays normal AC input, on battery power and fault conditions
elect items displayed on LCD screen. EPO (Emergency Power Off) button turns UPS output off and disables output -fail alarm can be silenced using alarm-cancel switch -signal a variety of operational conditions: low-battery, overload, shutdown, bypass and more Display: Displays normal AC input, on battery power and fault conditions
s signal a variety of operational conditions: low-battery, overload, shutdown, bypass and more Display: Displays normal AC input, on battery power and fault conditions
Display: Displays normal AC input, on battery power and fault conditions
aneous
aneous
aneous
aneous
3 x 72.39 x 101.09
x 28.50 x 39.80
5 x 49.02 x 84.07
19.3 x 33.1
,
x 3



Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+4 to +104 degrees Fahrenheit / -20 to +40 degrees Celsius	
Relative Humidity	Up to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	3595	
AC Economy Mode BTU / Hr. (Full Load)	1394	
Battery Mode BTU / Hr. (Full Load)	4359	
AC Mode Efficiency Rating (100% Load)	95%	
AC Economy Mode Efficiency Rating (100% Load)	98%	
Operating Elevation (ft.)	0 to 3280 feet, but derates 1% per 328 ft above 3280 ft	
Audible Noise	Less than 55dBA at 1m front side	
Operating Elevation (m)	1000 METERS FOR NOMINAL POWER (OVER 1000M THE POWER DE-RATING IS 1% PER 100M)	
COMMUNICATIONS		
Network Management Cards	SNMPWEBCARD; WEBCARDLX ; MODBUSCARD	
PowerAlert Software	Available via free download from www.tripplite.com/poweralert	
Communications Cable	DB9 cabling included	
Communications Interface	DB9 Serial; Slot for SNMP/Web interface	
LINE / BATTERY TRANSFER		
Transfer Time	No transfer time (0 ms.) in online, double-conversion mode	
Low Voltage Transfer to Battery Power (Setpoint)	Maintains continuous operation without using battery power during brownout/undervoltage conditions to 228VAC (70% load) / 300VAC (100% load). Below this point, output is maintained utilizing reserve battery power	
High Voltage Transfer to Battery Power (Setpoint)	Maintains continuous operation without using battery power during overvoltages to 477VAC, reducing output within 1% of nominal. Above this point, output is maintained utilizing reserve battery power	
FEATURES & SPECIFICATIONS		
Grounding Lug	Yes	
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Automatic inverter bypass; Hot swappable batteries; Auto Probe Monitoring (requires WEBCARDLX); Zero transfer time; On-Line/Double-Conversion	
Green Energy-Saving Features	High efficiency economy mode operation; Schedulable daily hours of economy mode operation	
IP68 Rated	No	
IP20 Rated	No	
STANDARDS & COMPLIANCE		



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

Product Certifications	IEC/EN 62040	
Product Compliance	RoHS; CE (Europe)	
WARRANTY		
Product Warranty Period (U.S. & Canada)	1-year limited warranty	
Product Warranty Period (International)	2-year limited warranty	
Product Warranty Period (Mexico)	2-year limited warranty	
3-Phase Warranty Statement	Tripp Lite 3-Phase UPS Factory Warranty	

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies